

---

# 2015 Spring - Information Theory

## Homework 8 (Due to May.22)

### Part 1: Alternative representation of a discrete channel

Let  $X$  and  $Y$  be respectively the input and the output of a discrete channel  $p(y|x)$ . Show that there exists a random variable  $Z$  and a function  $f$  such that  $Y = f(X, Z)$  and  $Z$  is independent of  $X$ . This is a generalization of the alternative representation of a BSC at the attachment.

Let  $X_i$  and  $Y_i$  be respectively the input and the output of the DMC  $p(y|x)$ . Then  $Y_i$  depends causally on  $X_i$  via  $Y_i = f(X_i, Z_i)$ , where  $Z_i$  is the noise random variable at time  $i$  which has the same distribution as  $Z$ , and  $Z_i$  is independent of all the random variables which have already been generated in the system.

### Part 2: Channel capacity

Derive the capacity of the parallel of two channels and the product of two channels.  $C_1$  with transition probability  $P_1$ ,  $C_2$  with transition probability  $P_2$

- product channel  $P(y|x) = \sum_k P_1(k|x) * P_2(y|k)$
- parallel channel  $P(y_1, y_2|x_1, x_2) = P(y_1|x_1)P(y_2|x_2)$

### Part 3: Order Statistics

Definitions Suppose again that we have a basic random experiment, and that  $X$  is a real-valued random variable for the experiment with distribution function  $F$  and probability density function  $f$ . We perform  $n$  independent replications of the basic experiment to generate a random sample  $X = (X_1, X_2, \dots, X_n)$  of size  $n$  from the distribution of  $X$ . Recall that this is a sequence of independent random variables, each with the distribution of  $X$ . Let  $X_{n,k}$ ,  $k(X)$  denote the  $k$ th smallest of element of the sample  $X$ . This statistics is called the order statistic of order  $k$ . Often the first step in a statistical study is to order the data; thus order statistics occur naturally. Our goal in this section is to study the distribution of the order statistics in terms of the sampling distribution. Note in particular that the extreme order statistics are the minimum and maximum values:  $X_{n,1} = \min(X_1, X_2, \dots, X_n)$ ,  $X_{n,n} = \max(X_1, X_2, \dots, X_n)$

Let  $G_{n,k}$  denote the distribution function of  $X_{n,k}$ . Define  $N_{n,y} = \#\{i \in \{1, 2, \dots, n\} : X_i \leq y\}$ ,  $y \in \mathbb{R}$

- Show that  $N_{n,y}$  has the binomial distribution with parameters  $n$  and  $F(y)$  for each  $y \in \mathbb{R}$ .
- Show that  $X_{n,k} \leq y$  if and only if  $N_{n,y} \geq k$  for  $y \in \mathbb{R}$  and  $k \in \{1, 2, 3, \dots, n\}$
- Use the results of Exercises 2 and 3 to show that  $G_{n,k}(y) = \sum_{j=k}^n \binom{n}{j} F(y)^j (1 - F(y))^{n-j}$ ,  $y \in \mathbb{R}$
- In particular, show that  $G_{n,1}(y) = 1 - (1 - F(y))^n$ ,  $y \in \mathbb{R}$ .
- In particular, show that  $G_{n,n}(y) = F(y)^n$ ,  $y \in \mathbb{R}$ .
- Suppose now that  $X$  has a continuous distribution. Show that  $X_{n,k}$  has a continuous distribution with probability density function  $g_{n,k}(y) = \binom{n}{k-1, 1, n-k} F(y)^{k-1} (1 - F(y))^{n-k} f(y)$ ,  $y \in \mathbb{R}$ .

### Part 4: Matlab Exercise

According to page220 page222 on the textbook, please construct a random decoder, a MAP decoder and a threshold decoder for the BSC and a finite block length. Think about the different between two decoders, and plot the error probability as a function of the crossover probability for different  $N$ .